



Frequency Domain Filtering II, LPC

Exercise 24 You have acquired the following signal:

t	0	1	2	3	4	5
$f(t)$	-2	0	1	-1	0	2

- (a) Compute the linear predictive coding (LPC) coefficients a_1 and a_2 of the signal and use them to determine $f(6)$.
- (b) Use the coefficients a_1 and a_2 to estimate the values $f(2)$, $f(3)$, $f(4)$ and $f(5)$, too.

Exercise 25 Programming Task: Extend the program to enhance the Saturn image from last exercise by the following parts:

- Use a windowing function (Hann and Bartlett window, plus another one of your choice from the lecture slides) and compare the results to the unwindowed version.
- Try to find a combination of filters (e.g., thresholding, morphology, ...) to automatically mask the spectrum components associated with the artifact.